

INSTALLATION

Before Installing this Product

1. Read all instructions before installing this product. Failure to follow instructions can damage the product or cause a hazardous condition.
2. Check the ratings given in the instructions and on the product to verify that the product is suitable for your application.
3. Installer must be a trained and experienced service technician.
4. Install the product in an area that is easily accessible for checkout and service.
5. After completing installation, use these instructions to check out product operation.

Installing the Retrofit Round Damper

Select a location for the damper in the ductwork. It is suggested that the RRD damper be at least 6 feet from the register for quiet operation.

1. Peel off the back of the cut-out template. Carefully align the template with the centerline of the duct. Apply template to the section of round ductwork where the damper is to be installed. Ensure that the template is parallel to the ductwork. It is suggested that the damper be installed with the motor under a horizontal duct to reduce twist to the duct. It may also be necessary to support the duct.
2. Drill a starter hole in the cut-out area of the template.
3. Cut out the area between the holes.
4. Slide the damper into the duct and secure it with the four supplied self-drilling mounting screws. Be careful to avoid over-tightening the screws as the duct may be pulled out of round. See Fig. 3.




Fig. 3. Inserting RRD damper into duct.

WIRING

Wiring the Motor Actuator

Connect the motor to the zone control panel 18 or 20 gauge wire. The motor terminals are labeled M1 for common, M4 for open, and M6 for closed. Connect the motor terminals to corresponding terminals on zone control panel for each zone. See Fig. 4–6 for hookups.

Multiple RRD dampers can be wired to one zone when wired in parallel. See Fig. 5 for wiring multiple dampers together in a daisy chain manner or Fig. 6 using wire nuts. See Table 1 for

the maximum number of dampers that can be connected to each zone control panel. Note that this is the total number of dampers connected to all the zones of a zone control panel; the maximum dampers per zone is 14. If more than 14 dampers are on one zone, a Slave Damper Control Relay (SDCR) must be used.

When more than the maximum number of dampers allowed per panel are necessary, a SDCR must be used. The SDCR is an isolation relay that is powered by a separate transformer so that it relieves the panel of this additional load. When a SDCR is used, the dampers of that zone may either be all connected to the SDCR, or some dampers may be wired to the SDCR and the remainder to that zone's damper terminals.

Maximum number of dampers per zone.

	One 40 VA Transformer	Two 40 VA Transformers (or One 75 VA)
TrueZONE® Panels*	13	27
W8835*	12	26
SDCR	15	28

*Maximum of 14 dampers per zone




Fig. 4. RRD wired to zone control panel.




Fig. 5. Wiring multiple RRD dampers in daisy chain fashion.

RETROFIT ROUND DAMPER (RRD)




Fig. 6. Wiring multiple RRD dampers using wire nuts.

ADJUSTMENTS

Manual Blade Adjustment

To verify correct range of motion, depress the manual blade adjustment button. While this is pressed, the gears are disengaged, allowing the blade to be manually opened or closed by turning the damper blade shaft. See Fig. 1.

Position Indicator

The position indicator (shown in Figure 1) points toward the position of the damper blade to identify if the blade is open, closed, or at an intermediate position. A slot at the end of the damper blade shaft also indicates blade position.

Range stops

The RRD damper motor can be adjusted to prevent complete closure of the blade. This is useful in zone systems where it is not possible to install a bypass damper.

To set the range stop to prevent complete closure:

1. Locate the range stop adjustment screw on the top of the motor to the right blade shaft. This is at the extreme counter-clockwise end of travel.
2. Using a small Phillips head screwdriver, loosen the set screw.
3. Move the end-stop block to the new position
4. Secure the set screw.
5. Verify the new range of motion while depressing the manual blade release button.

TROUBLESHOOTING

Damper operates backwards	Verify correct damper wiring as shown in Fig. 4–6. Also verify that the Rotation Direction screw is in the "0" position as shown in Figure 1.
Damper does not operate	<ol style="list-style-type: none"> 1. Verify damper wiring using checkout methods listed in this document. 2. Verify that the duct is round and not making the blade stick. Depress the manual blade release button and manually turn the blade shaft to verify smooth opening and closing operation.

Automation and Control Solutions

Honeywell International Inc.
1985 Douglas Drive North
Golden Valley, MN 55422

Honeywell Limited-Honeywell Limitée
35 Dynamic Drive
Toronto, Ontario M1V 4Z9
customer.honeywell.com

Rotation Direction Adjustment

The rotation direction screw (Shown in Figure 1) reverses the direction the damper operates. It should be left in the "0" position to open when M4 is powered and close when M6 is powered.

CHECKOUT

⚠ CAUTION

Possible Equipment Damage

Do not manually open or close the damper unless the manual blade release button is depressed.

To check out the RRD damper using 24 VAC transformer:

1. Connect 24 VAC common to the M1 (common) terminal on the actuator.
2. Connect 24 VAC hot to the M6 terminal to close the damper.
3. Observe the blade move clockwise and stop in the closed position.
4. Remove the 24 VAC hot wire from the M6 terminal.
5. Connect the 24 VAC hot wire to the M4 terminal.
6. Observe the blade move counter-clockwise and stop in the open position.
7. This verifies correct operation.

Alternatively, if the damper is wired to a TrueZONE HZ432 or HZ322 panel, the damper checkout process may be used to verify damper operation.

Honeywell