

Rev	ECO/EN#	Completed By	Details/Description	MASCO CORPORATION PLUMBING PRODUCTS DIVISION	Do Not Scale, All Dimensions in Inches (Millimeters) Fractional Tol ±1/8" (± 2 mm) unless specified otherwise For reference only, not for reproduction purposes.	LINE TYPE BROKEN _____ FOLDING - - - - - REVERSE-----	CUTTING DIE # XXXXXX	BOXES PER TIER XXXXXX	BOXES PER PALLET XXXXXX	PART NET WEIGHT XXXXXX		
A				THIS DOCUMENT AND ALL THE DATA IT CONTAINS IS THE SOLE AND EXCLUSIVE PROPERTY OF DELTA FAUCET COMPANY, DIVISION OF MASCO CORPORATION OF INDIANA AND SHALL NOT BE DISCLOSED TO OTHERS WITHOUT THE EXPRESS CONSENT OF DELTA FAUCET COMPANY. COPYRIGHT © 2018 MASCO CORP. of INDIANA			SCALE ("2:5")	CREATE DATE 4/10/19	PREPARED BY E. Weartz	APPROVED BY SR		
B												
C				MATERIALS 80# silk cover		OUTSIDE DIMENSION 5.75" x 34.5"	MATERIAL SIZE	JOINT METHOD none	PART DESCRIPTION Marketing Insert	PART NUMBER 104181	REV. A	PAGE 1 of 2

Notes Section:

COMMAND THE ROOM

Brizo Voice Activation Technology allows you to dispense the exact amount of water you need, completely hands-free. Just command your faucet to turn on and off, warm the water, dispense a metered amount or create custom container amounts—luxury answers to you.

BRIZO

10418 Rev. A 03/12/2019

MATERIALS REQUIRED

These instructions begin with an installed Brizo SmartTouch® faucet\*. If you have not installed your faucet yet, please follow the instructions for faucet installation prior to installing your Brizo VoiceIQ™ Module. You will also need a smartphone or tablet and the following to complete the set-up:

- 

**A POWER SOURCE**  
Under the sink.  
Not controlled by a switch.
- 

**A CONNECTED HOME DEVICE**  
Amazon® Alexa™ or Google® Assistant.
- 


**A HOME WI-FI SYSTEM**  
And your login information.

Before you begin, remove the batteries from your SmartTouch® solenoid.


For more product details, installation assistance and other helpful information, visit [brizo.com/voiceactivation](http://brizo.com/voiceactivation).

\*manufactured after 01/01/18

INSTALLATION INSTRUCTIONS



**STEP 1.**  
Turn off your water supply.




**STEP 2.**  
Remove the plastic clip from the bottom of your existing solenoid.




**STEP 3.**  
Remove the existing hose by gently pulling it downward.




**STEP 4.**  
Slide the new VoiceIQ™ Module unit onto the bottom of your existing solenoid.




**STEP 5.**  
Swivel the retainer clip upward and click it into place.



**STEP 6.**  
Slide the hose onto the VoiceIQ™ Module and secure it with the retaining clip.




**STEP 7.**  
Connect the ethernet cable to the voice module and the existing solenoid.




**STEP 8.**  
Connect the power supply to the solenoid and to an outlet that is not controlled by a switch. Reinstall SmartTouch™ solenoid batteries\* and turn on water supply.

\* In case of power outage, touch activation will revert to battery power.

INSTALLATION INSTRUCTIONS (CONT)


 Connect your Smartphone or tablet to your VoiceIQ™ Module's Wi-Fi signal, **"BRIZO-ABC"**. Your VoiceIQ™ Module will have a unique identifier in the name of the Wi-Fi connection, shown here as "ABC".

 Open a browser and enter the URL **10.10.10.1** for product setup. Follow the steps on screen.

 Bookmark **device.brizo.com** for easy access to the Web app, where you can see settings, FAQs and a list of voice commands.

VOICEIQ™ MODULE LED COLOR INDICATORS

This light can be found on your VoiceIQ™ Module under the sink, not at the faucet base.

 **BLINKING GREEN**  
Wi-Fi setup mode: indicates the VoiceIQ™ Module is trying to connect to Wi-Fi. If blinking continues for more than 3 minutes, you may need to reconnect it to your home Wi-Fi.

 **BLINKING RED**  
Indicates that the required AC power is not connected (blinks once every 5 seconds).

 **SOLID GREEN**  
Indicates a successful connection to the Wi-Fi.

 **SOLID RED**  
Indicates an interrupted or failed connection.

TROUBLESHOOTING TIPS

If your VoiceIQ™ Module is blinking a red light every 5 seconds, this indicates an issue with the power supply. Verify that the outlet you've plugged your module into isn't connected to your garbage disposal switch by plugging something else into the outlet (lamps and other lights work best, but anything that lights up or makes noise and doesn't have a backup battery will work), then switching your garbage disposal on and off. If the item plugged into the outlet only works with the garbage disposal switched on, your outlet is connected to your garbage disposal and isn't compatible with your VoiceIQ™ Module.

If you can't locate BRIZO-ABC on your list of available Wi-Fi networks, check for a flashing green light on your VoiceIQ™ Module under the sink. If the light is blinking green, re-scan for Wi-Fi networks on your mobile device. If the light is blinking red, see the above troubleshooting tip about power supply.

If the VoiceIQ™ Module setup page fails to load on your mobile device after entering 10.10.10.1, check the following:

- A.** If the LED light on your VoiceIQ™ Module is blinking green, it's still in Wi-Fi setup mode. Re-scan for Wi-Fi networks on your mobile device and connect to "Brizo-ABC" ("ABC" is used here to mark your module's unique identifier code).
- B.** If the LED light on your VoiceIQ™ Module is blinking red, it isn't connected to a power source. See the first troubleshooting tip, above.
- C.** Turn off cellular data on your mobile device, but leave Wi-Fi on, then refresh the webpage.

TROUBLESHOOTING TIPS (CONT)

If device fails to connect after entering Wi-Fi network name and password and the LED on voice module is solid red, check the following:

- A.** Double check that the password for your VoiceIQ™ Module's Wi-Fi was entered correctly.
- B.** The VoiceIQ™ Module works with 2.4 GHz Wi-Fi. If your router has both 2.4 GHz and 5.0 GHz, please make sure you use 2.4 GHz. When scanning for Wi-Fi networks on your mobile device, only the 2.4 GHz network will appear.

CONTINUOUS SUPPORT

We're here to help. You'll find a full list of frequently asked questions at **device.brizo.com**. You're also welcome to call our customer solutions line at **833-297-8482**.

For warranty information visit [www.brizo.com/customer-support/warranty-and-returns](http://www.brizo.com/customer-support/warranty-and-returns)

The VoiceIQ™ Module is designed to work with Brizo SmartTouch® Faucets manufactured after 01/01/2018.

VOICE ACTIVATION

by **BRIZO**

Notes Section:

COLOR #1 CYAN	COLOR #2 MAGENTA	COLOR #3 YELLOW	COLOR #4 BLACK	COLOR #5 PMS 424 C	COLOR #6 -	COATING Coating Aqueous Silk	PRINTING -	PAGE 2 of 2
------------------	---------------------	--------------------	-------------------	-----------------------	---------------	------------------------------------	---------------	----------------