# **KOHLER**<sub>®</sub>

## Verdera® lighted mirror, 40" W x 33" H K-99573-TLC

#### Features

- Internal LED light guides provide optimally bright bathroom vanity lighting for grooming tasks.
- Brightness at 2200 lumens ensures consistent lighting with no hot spots or dark spots. Produces 65 lumens per watt.
- Approx. 3000 Kelvin light appearance delivers a neutral light ideal for overall bathroom aesthetics as well as tasks.
- Minimum 90 CRI (color rendering index) lets you see yourself in the truest light for makeup application, grooming and skin care.
- Integrated LED bulbs have an estimated life expectancy of 59,000 hours.
- Compatible with wall-mount LED dimmers (not included), which allows you to control lighting from multiple locations in the space.
- Pivoting side panels allow you to direct light for specific tasks.

#### Material

• Anodized aluminum construction with a durable rust- and chip-resistant finish.

#### Installation

- Includes mounting hardware for surface installation.
- Hang-and-secure mounting system for easier surface-mount installation.
- Recommend professional electrician installation.

#### **Recommended Products/Accessories**

K-23723 Faucet cleaner



## **Codes/Standards**

UL 962 C22.2 No. 0 CA Title 24 JA8


## KOHLER<sup>®</sup> One-Year Limited Warranty


See website for detailed warranty information.





# Verdera® lighted mirror, 40" W x 33" H K-99573-TLC





#### **Required Electrical Service**

One circuit required, protected with Class A Ground-Fault Circuit-Interrupter (GFCI). Outside North America, this device may be known as a Residual Current Device (RCD).

Lights: 120 V, 15 A, 60 Hz

#### **Technical Information**

All product dimensions are nominal.

Mirror type: Wall-mount pivot

Electrical component Lights: 120 V, 0.8 A, 60 Hz rating:

#### Notes

Install this product according to the installation instructions.

Select the type of fastener based on the wall material. A minimum 20 lb (9.07 kg) load bearing fastener is recommended.

Install the fastener to a stud to avoid possible property and product damage.

A dimmer switch is required. This product is compatible with most residential dimmer switches intended for incandescent and dimmable LED bulbs.

